

FLEXIBLE BATTERY / STARTER CABLE

Specification:

Conductor: 196/0.4

Amp Cap: 170

TW 800551

Cross Section:

Area: **25sq.mm**

Nominal O/D: 9.8mm

E3010 9.97 per mtr

Usage:

Battery starter



Specification:

Conductor: 475/0.40

Amp Cap: 415

TW800581

Cross Section:

Area: 60sq.mm

Nominal O/D: 14.6mm

E3013 20.18 per mtr

Usage:

Battery starter, winches

Specification:

Conductor: 315/0.40

Amp Cap: 300

TW800561

Cross Section:

Area: **40sq.mm**

Nominal O/D: 12.2mm

E3011 15.64 per mtr

Usage:

Battery starter, winches



Specifications

Conductor: 905/0.30

Amp Cap: 485

TW800591

Cross Section:

Area: 70sq.mm

Nominal O/D: 15.4mm

E3014 22.16 per mtr

Usage:

Heavy duty



Specification:

Conductor: 396/0.40

Amp Cap: 345

TW 800571

Cross Section:

Area: **50sq.mm**

Nominal O/D: 13.3mm

E3012 16.99per mtr

Usage:

Battery starter, winches



Specification:

Conductor: 684/0.4

Amp Cap: 500

TW800601

Cross Section:

Area: **95sq.mm**

Nominal O/D: 17.9mm

E3015 30.35 per mtr

Usage:

Suggestions: Heavy duty

TWIN CABLE THIN WALL



Specification:

Conductor: 2 x 32/0.20

Amp Cap: 16.5

TW800833

Cross Section:

Area: 2 x 1.0sq.mm

Nominal O/D: 3.5 x 5.5mm

Usage:

Interior and navigation lights

E3021 1.11 per mtr

E3021 35.51 30mtr coil



Specification:

Conductor: 2 x 28/0.30

Amp Cap: 25.0

TW800843

Cross Section:

Area: 2 x 2.0sq.mm

Nominal O/D: 3.8 x 6.6mm

Usage:

Searchlights etc.

E3022 1.85 per mtr

E3022 55.50 30mtr coil



Specification:

Conductor: 2 x 44/0.30

Amp Cap: 27.50

Cross Section:

Area: 2 x 3.0sq.mm

Nominal O/D: 4.4x 7.6mm

Usage:

Suggestions: Battery feed.

E3023 3.09 per mtr

E3023 92.74 30mt coil

